Technical Support

For Connection support, contact:

TIP: If you forget your PIN, sign in to the Cisco PCA and browse to the Personal Preferences page in the Messaging Assistant to change it.

The Cisco PCA URL is:

cisco.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

© 2012 Cisco Systems, Inc. All rights reserved.

OL-21689-01

cisco.

RELEASE 9.X



Cisco Unity Connection Voice Commands

Published June 2012

This card lists frequently used voice commands for managing Cisco Unity Connection messages and user preferences by phone.

Accessing Connection

1. Call Cisco Unity Connection. From your desk phone, dial:

From another phone within your organization, dial:

From outside your organization, dial:

- If you are calling from another phone within your organization or from outside your organization, press * when Connection answers.
- **3.** If prompted, enter your Cisco Unity Connection ID (usually your desk phone extension), and press #.
- 4. Enter your PIN, and press #.

Playing Messages

While listening to the Main menu, say:

"Play messages" (for all messages)

Or a combination of these options $``Play \label{eq:play}$

- <new or saved or deleted>
- «urgent or private or urgent and private»
- <voice messages or emails* or faxes* or external messages* or receipts or meetings*>"

Or a combination of these options, for messages from Connection users "Play

- <new or saved or deleted>
- «urgent or private or urgent and private»
- messages from <name of Connection user>"

Message Playback

During or after message playback, say:

"Repeat message"

"Next message"

"Previous message"

"Save"

"Delete"

"Reply" or "Reply to all"

"Forward"

"Mark new"

"Message properties"

"List recipients" (Connection 8.5 and later) "Call sender"*

"Resend" (to resend the original message after you receive a nondelivery receipt)

Sending a Message

While listening to the Main Menu, say: "Send a message"

"Send <urgent or private or urgent and private> message to <name of Connection user>"

After addressing and recording the message, say:

"Send"

"Edit message"

"Review message properties" (to hear only message properties)

"Review message" (to hear the recorded message and message properties) "Edit recipients"

"Set <urgent or private or urgent and private>"

"Cancel <urgent or private or urgent and private>"

"Set receipt"

"Cancel receipt"

"Future delivery"

"Cancel future delivery"

Placing Calls

While listening to the Main Menu, say:

"Call <name of Connection user>"

"Call <extension>" (Say each digit individually. For example, say "One, zero, zero" not "One hundred.")

"Call <name of contact> at <home or work or mobile>"

Universal Commands

Say these commands anytime:

"Cancel"

"Main menu" (to return to Main menu)

"Repeat" (to repeat message or menu prompts)

"Pause" or "Resume"

"End call" or "Goodbye"

"Help" (for help with voice commands)

Other Commands

While listening to the Main menu, say:

"Play <greeting name> greeting"

"Record <greeting name> greeting"

"Turn on <greeting name> greeting" (to enable the greeting indefinitely)

"Turn on <greeting name> greeting until <date>"

"Turn off <greeting name> greeting"

"Change my PIN"

"List my number in the directory"

"Do not list my number in the directory"

"Play my recorded name"

"Change my recorded name"

"Empty Deleted Items folder"*

"Touchtone conversation" (switches to phone keypad input for remainder of call)

"Setup options" (switches to phone keypad input; to switch back, keep pressing * until you hear "Voice command conversation") "Tutorial" (to access a set of tutorials on working with voice commands)